

SOLO-KP

SOLO-KP LCD

COMPACT MULTI-APARTMENT GSM DOOR ENTRY UNIT



USER MANUAL

Contents

1	FOR YOUR SAFETY	3
2	INTRODUCTION.....	4
3	SOLO-KP / SOLO-KP LCD FEATURES AND APPLICATIONS.....	5
4	START UP.....	6
5	LED INDICATION.....	7
6	CONNECTION DIAGRAM	8
7	SOLO-KP (LCD) UNIT MANAGEMENT.....	9
8	SOLO-KP (LCD) FUNCTIONS WITH PROGRAMMING INSTRUCTIONS.....	10
8.1	WEB SERVER - LOG IN.....	10
8.2	WEB SERVER – ADDING UNITS TO USER PROFILE.....	11
8.3	WEB SERVER-UNIT MANAGEMENT	13
8.4	INTERCOM CONFIGURATION	14
8.5	PIN ACCESS.....	16
8.6	VIDEO PIN ACCESS (ANPR ACCESS).....	18
8.7	DIGITAL INTERFACE.....	19
8.8	CALLER ID ACCESS.....	20
8.9	OUTPUTS SETTINGS	21
8.10	TIMER-TIMED CONTROLLED OUTPUT.....	23
8.11	ADMINISTRATION.....	25
8.12	EVENT LOGGING	27
8.13	MISC.....	28
9	WIEGAND INTERFACE DATA FORMATS	29
9.1	WIEGAND 26 BIT, DIFFERENT DATA FORMATS	29
9.2	WIEGAND 30 BIT, DIFFERENT DATA FORMATS	30
10	CONTACTS	31

Figures

Figure 1: SOLO-KP (LCD): Connection diagram	8
Figure 2: WEB Server-Sign In page	10
Figure 3: WEB Server-Main page select ADD mode	11
Figure 4: WEB Server-Main page adding SOLO-KP (LCD) units	12
Figure 5: WEB Server-Unit management window	13
Figure 6: WEB Server-Intercom settings.....	14
Figure 7: WEB Server- PIN Access configuration	16
Figure 8: WEB Server-VIDEO PIN Access configuration.....	18
Figure 9: WEB Server-Wiegand interface support.....	19
Figure 10: WEB Server-Caller ID Access	20
Figure 11: WEB Server-Output setting.....	21
Figure 12: WEB Server-Timer setting →Day mode.	23
Figure 13: WEB Server-Timer setting →Week mode.....	23
Figure 14: WEB Server-Notification numbers	25
Figure 15: WEB Server-Input alarm configuration	25
Figure 16: WEB Server-Log event	27
Figure 17: WEB Server-Misc	28

Tables

Table 1: WEB Server-PIN entry parameters.....	17
Table 2: WEB Server-Timer setting, output mode options	24
Table 3: Wiegand 26: Mode 0.....	29
Table 4: Wiegand 26: Mode 1.....	29
Table 5: Wiegand 26: Mode 2.....	29
Table 6: Wiegand 26: Mode 3.....	29
Table 7: Wiegand 30: Mode 0.....	30
Table 8: Wiegand 30: Mode 1.....	30
Table 9: Wiegand 30: Mode 2.....	30
Table 10: Wiegand 30: Mode 3.....	30

1 FOR YOUR SAFETY

SWITCH ON SAFELY

Do not switch the unit on when use of wireless phone is prohibited or when it may cause interference or danger.

INTERFERENCE

All wireless phones and units may be susceptible to interference, which could affect performance.

SWITCH OFF IN HOSPITALS

Follow any restrictions. Switch the unit off near medical equipment.

SWITCH OFF IN AIRCRAFT

Follow any restrictions. Wireless devices can cause interference in aircraft.

SWITCH OFF WHEN REFUELING

Do not use the unit at a refueling point. Do not use near fuel or chemicals.

SWITCH OFF NEAR BLASTING

Follow any restrictions. Do not use the unit where blasting is in progress.

USE SENSIBLY

Use only in the normal position as explained in the product documentation. Do not touch the antenna unnecessarily.

2 INTRODUCTION

SOLO-KP (SOLO-KP LCD) is a simple but powerful GSM intercom communication system designed to ensure low-cost, simple to install/use, reliable and single box solution for intercom application. It is designed for unlimited range, wire free GSM intercom, pin code access, caller ID control and Wiegand access support.

SOLO-KP and SOLO-KP LCD units are built for multi-apartment solutions.

Optional SOLO-KP (LCD) supports alarm detection, stay-alive messages, credit detection etc...

NOTE

SOLO-KP is derivative of the SOLO-KP LCD and it is a unit without LCD support.

3 SOLO-KP / SOLO-KP LCD FEATURES AND APPLICATIONS

Features:

- ⇒ Built-in GSM (LTE) module
 - ⇒ For up to 200 (500, 1000) apartments (2 phone numbers for each apartment),
 - ⇒ Keypad Access entry support (up-to 1000 PIN codes)
 - ⇒ Standalone ANPR system with (up-to 1000 licence plates)
 - ⇒ Caller ID numbers control (up-to 1000 caller ID numbers)
 - ⇒ 2 Inputs Wiegand receiver (up-to 1000 receivers)
 - ⇒ 2 outputs (relay supported)
 - ⇒ LCD screen for user called (only valid in SOLO-KP LCD)
-
- ⇒ Programming by WEB server

Applications:

- ⇒ Single box, wire free intercom solution
- ⇒ Remote gate opener – Caller ID number recognition
- ⇒ Standalone ANPR parking system
- ⇒ Simple (Wiegand) access system

4 START UP

SOLO-KP (LCD) unit accepts a standard GSM SIM card from any network.

**VERY
IMPORTANT**

USE THE MICRO SIM CARD



WARNING

DO NOT insert or remove the SIM card while the unit is powered ON!!

IMPORTANT

Before inserting SIM card to unit make sure the PIN code is removed!!

- ⇒ Insert SIM card in SOLO-KP (LCD) unit.
- ⇒ Connect power cable to SOLO-KP (LCD) unit (YOU MUST POWER THE SOLO-KP (LCD) UNIT WITH THE POWER SUPPLY INCLUDED). Do not power with any other power supply.
- ⇒ Power up the unit.
- ⇒ Wait until LED1 (Blue) starts flashing. This is set in around 30 – 45 seconds.
- ⇒ SOLO-KP (LCD) unit is now ready to operate.

NOTE

SOLO-KP (LCD) device will “beep” in 15s interval until the device is not in normal operation.

5 LED INDICATION

Blue LED (LED1)

- Indicates the level of the GSM signal from 1 to 5 LED flashes (1 is weak signal, 5 is excellent signal)

Red LED (LED2)

- GSM module Activity

Yellow LED (LED3)

- Short flashing indicates that the GSM module is ON, but it is not yet connected on the GSM network. After connection, yellow led is flashing with short pulse (0,5s) ON and a long pulse OFF (5s).

6 CONNECTION DIAGRAM

Before connection the SOLO-KP (LCD) please take a look at connection diagram.




Figure 1: SOLO-KP (LCD): Connection diagram

IMPORTANT

DO NOT USE Power out (12V AUX) for electric lock driving! Use separate power source for door electric lock!

7 SOLO-KP (LCD) UNIT MANAGEMENT

Unit supports different types of management (programming):

- ⇒ Unit can be programmed remotely by using WEB server access.
- ⇒ Unit can be programmed remotely by SMS commands (Optional).

8 SOLO-KP (LCD) FUNCTIONS WITH PROGRAMMING INSTRUCTIONS

As mentioned in previous chapters SOLO-KP (LCD) unit can be programmed in various ways, this document will focus on most common programming way: WEB programming.

IMPORTANT

SIM card in the SOLO-KP (LCD) unit **MUST have DATA PLAN** to be able to use WEB programming!

8.1 WEB SERVER - LOG IN

The web server can find under the address: <https://www.easyset.eu/>.

Log in

Sign Up Back to site

Please sign in with one of your existing accounts, or [create a new account](#) on EasySet and sign in below:

f g
or

Login: user1

Password: *****

remember me:

Forgot your password? Log in

When using this site, you agree to our [terms of service](#)

Figure 2: WEB Server-Sign In page

User must first use the Sign IN section to create working profile on the server. The profile can be created by using social login like Facebook, Google account or Twitter. If user lacks any of the social profile it can proceed to Sign UP page use standard user name and password entry.

NOTE

Server support Firefox, Google Chrome, Safari.

8.2 WEB SERVER – ADDING UNITS TO USER PROFILE

After login the user will be diverted to WEB server main window. This page is used to add/remove/search for SOLO-KP (LCD) units from the user's profile.

Select “+” sign to select ADD SOLO-KP (LCD) units to user's profile.





Figure 3: WEB Server-Main page select ADD mode



The screenshot shows a modal window titled "Add a new device" with a close button (X) in the top right corner. The form contains the following fields:

- Name: A text input field.
- IMEI: A text input field.
- Phone number: A text input field.
- SIM provider: A dropdown menu.
- Location: A text input field.

At the bottom of the form, there are two buttons: "Cancel" and "Add".

Figure 4: WEB Server-Main page adding SOLO-KP (LCD) units

User than provides required data:

- **Name:** Name for the added unit - mandatory information.
- **IMEI:** Identification number of the unit, can be found in the enclosure of the unit - mandatory information. The IMEI is located on the cellular chip and also should be on the card board box of the SOLO-KP (LCD).
- **Phone Number:** The telephone number of the SIM card in the SOLO-KP (LCD) unit - mandatory data.
- **SIM provider:** Information needed to enable data connection between the server and the unit. Selectable from the drop-down menu - mandatory data. If the provider is not on the list, please contact the producer.
- **Location:** Notification field, used by the user to provide extra data for its own information - optional data.

First building of the unit data-base may take a few minutes.

8.3 WEB SERVER-UNIT MANAGEMENT

After the SOLO-KP (LCD) unit is added to user database, the user can change the configuration of the specific unit.

All changes made by the user are listed in the **Change Log** window. **By clicking Send to device button ALL changes are sending to the unit.**




Figure 5: WEB Server-Unit management window

8.4 INTERCOM CONFIGURATION

Primary function of the SOLO-KP (LCD) unit is intercom support for multiapartment use. Selecting (calling) apartment number is achieved on two ways

- entering apartment number on the keypad and pressing # at the end.
- Selecting appropriate name with UP/DOWN arrows beside the LCD and press the CALL button (only valid in SOLO-KP LCD)

Either of the actions will start a voice call procedure to **Phone number 1** and **Phone number 2**. After the call is answered the called user has the option to trigger the output by pressing “11” for opening *Output 1* or “21” for triggering *Output 2*.

Management of the intercom function is found under **Intercom** tab.




Figure 6: WEB Server-Intercom settings.

Intercom management parameters:

- **Apartment number:** Dial code of the apartment.
- **Phone number 1 & Phone number 2:** 2 Numbers that the SOLO-KP (LCD) unit will call when appropriate apartment is selected on the keypad or selected on the LCD screen.
- **User name:** User name shown on the LCD screen (only valid in SOLO-KP LCD)
- **Driver output:** The output that will be triggered if the user with **Phone number 1** or **Phone number 2** will call the unit (Caller Id function)

- **Delay between calls:** Ring time (in seconds) for **Phone number 1** and **Phone number 2**. After the ring time for **Phone number 1** expires and the call is not answered the unit will call **Phone number 2**.
- **Line open time:** Defines maximum in-connection time in second before the unit will automatically disconnect the call.

Voice call setting

- **Microphone level:** Increasing the level will increase the sensitivity of the unit microphone decreasing will decrease the sensitivity.
- **Speaker level:** Increasing the level will increase the volume of the unit speaker, decreasing will decrease the level of the speaker.
- **Ringing sound:** By selecting *Playing* the unit will play the dial tone in the connection phase of the call, by selecting *Muted* the unit will not play any sound in the connection phase of the call.
- **On activate input:** By selecting *Play beep sound (buzzer)* the unit will provide audio feedback (buzzer BEEP) when the apartment entry is selected, by selected *Muted* unit will provide no audio feedback when the apartment entry is selected.

8.5 PIN ACCESS

On-board keypad and external Wiegand devices are used for access by entering PIN codes.

WEB server supports simplified and advance view/configuration of the PIN code. In simplified view only basic configuration of PIN code is possible.

PIN codes support different modes/area of operation:

- Basic control mode
- Access mode
- Restricted access mode

View of the PIN code configuration will be shown according to selected PIN code mode.

Basic Control mode: The single PIN code can drive up to four pre-programmed Outputs with all possible restrictions (counter and time).

Access mode: In this mode, each Wiegand Input is dedicated to one output, the PIN code entered on Wiegand 1 is driving the relay Output 1, PIN code entered on Wiegand 2 is driving relay output 2. All possible restrictions (counter and time) apply to PIN codes.

Restricted Access mode is the same as the Access mode, except that the user can determine which Output is managed by the same PIN code. All possible restrictions (counter and time) apply to PIN codes.

PIN code configuration options

Position	PIN	User name	Counter limit	PIN counter	Time limit	Time limit mode	Start time	End time	Start date	End date	Selected days	Outputs	Sources	Notify	Latch
PIN1	1234	Jo test	<input type="checkbox"/>	0	<input type="checkbox"/>	Work Time	00:00	00:00			Mon Tue Wed Thu Fri Sat Sun	Configure	Configure	<input type="checkbox"/>	<input type="checkbox"/>
PIN2	0		<input type="checkbox"/>	0	<input type="checkbox"/>	Work Time	00:00	00:00			Mon Tue Wed Thu Fri Sat Sun	Configure	Configure	<input type="checkbox"/>	<input type="checkbox"/>
PIN3	0		<input type="checkbox"/>	0	<input type="checkbox"/>	Work Time	00:00	00:00			Mon Tue Wed Thu Fri Sat Sun	Configure	Configure	<input type="checkbox"/>	<input type="checkbox"/>
PIN4	0		<input type="checkbox"/>	0	<input type="checkbox"/>	Work Time	00:00	00:00			Mon Tue Wed Thu Fri Sat Sun	Configure	Configure	<input type="checkbox"/>	<input type="checkbox"/>
PIN5	0		<input type="checkbox"/>	0	<input type="checkbox"/>	Work Time	00:00	00:00			Mon Tue Wed Thu Fri Sat Sun	Configure	Configure	<input type="checkbox"/>	<input type="checkbox"/>

Figure 7: WEB Server- PIN Access configuration

Configuration options	Description
PIN	PIN code value
User name	Name of the user
Counter limit	Enable/Disable counter limitation (consecutive use)
Pin counter	Counter limit value
Timer limit	Enable/Disable timer limitation
Timer mode	Work Time: time limitation on daily bases, no calendar limitation Full Time constraint: absolute time limitation time + calendar limitation
Start Time	Start time of PIN code validity (hours + minutes)
End Time	End time of PIN code validity (hours + minutes)
Start date	Start day of PIN code validity (only valid for Full Time Constraint option)
End date	End day of PIN code validity (only valid for Full Time Constraint option)
Selected days	PIN code validity selection for day of a week
Outputs	Selection of the output for PIN code to trigger
Sources	Allowed input source for PIN code
Notify	When PIN code is used, administrator numbers will be notified
Latch	This selection forces output into latching mode of operation

Table 1: WEB Server-PIN entry parameters.

8.6 VIDEO PIN ACCESS (ANPR ACCESS)

Video pin (LICENCE PLATE number) access is use together with Hikvision or Tattile ANPR camera. Along with these cameras user can build a simple but powerful standalone ANPR system.

VIDEO PIN ACCESS (ANPR system) support different modes/area of operation:

- Basic control mode
- Access mode
- Parking mode

View of the VIDEO PIN code configuration will be shown according to selected VPIN mode.

Basic Control mode: The single VIDEO PIN code can drive up to four pre-programmed Outputs with all possible restrictions (counter and time).

Access mode: In this mode, each Wiegand Input is dedicated to one output, the VIDEO PIN code entered on Wiegand 1 is driving the relay Output 1, VIDEO PIN code entered on Wiegand 2 is driving relay output 2. All possible restrictions (counter and time) apply to VIDEO PIN codes.

Parking mode is similar as the Access mode, but in addition it support a free parking option and inclusion to a bigger parking system (with the use of cloud parking solution EasyPin)

VIDEO PIN code configuration options are the same as PIN code configuration options.




Figure 8: WEB Server-VIDEO PIN Access configuration

8.7 DIGITAL INTERFACE

SOLO-KP (LCD) unit has onboard support for 2 Wiegand based devices. Addition to 2. Wiegand inputs the device can be also used as a Wiegand device for integration into bigger access device. In this case numbers calling the SOLO-KP (LCD) unit will be transferred, over Wiegand interface, to access system.

Configuration of first Wiegand interface is found in **Digital interface** tab.




Figure 9: WEB Server-Wiegand interface support.

Wiegand input 1 and Wiegand input 2

- **Mode:** Select appropriate data formatting (Advise unit provider for more info if needed, mode 2 is most common setting)
- **Facility code:** User can *Enable* or *Disable* facility code field.

Wiegand output

- **Wiegand type:** Select length of the Wiegand data (W26 is most common setting)
- **Data format:** Select appropriate data formatting (Advise unit provider for more info if needed)
- **Front parity:** Front parity type
- **Trailing parity:** Trailing parity type
- **Facility code:** Facility value to be used for sending

NOTE

See Chapter **Napaka! Vira sklicevanja ni bilo mogoče najti. WIEGAND INTERFACE DATA FORMATS** for detailed explanation of different data format options.

8.8 CALLER ID ACCESS

Caller ID access is a very simple way to control relay output defined in **Caller ID output** setting. User will by calling in the SOLO-KP (LCD) unit trigger defined output.

Settings for this function are found in the **Caller ID #** tab.




Figure 10: WEB Server-Caller ID Access

General settings:

- **Caller ID security mode:** User can select between 3 options:
Caller ID Disabled deactivates caller ID function – all numbers are restricted
Caller ID for specific users will limit the caller ID function only to the numbers on the list.
Caller ID always ON will allow all user that know the number of the unit to open defined output. In last option the user doesn't need to be on the list to trigger the output
- **Caller ID output:** Selecting the output that will be triggered in Caller ID function.
- **Phone number:** Number of the user that will be used to open the relay selected by Caller ID output.
- **User:** Name of the user.

NOTE

Selection *Caller ID always ON* will allow anybody with the knowledge of the unit number to trigger the output by calling the unit. Use this setting with caution.

8.9 OUTPUTS SETTINGS

The behavior on the outputs is defined in the **Output tab**.




Figure 11: WEB Server-Output setting

Output 1 and Output 2

- Output (relay) mode:** User can select between 3 options
 - Disable*-Output is disabled.
 - Latching*-Output is in latching mode. First Caller ID or PIN entry will activate the output, second Caller ID or PIN entry will deactivate the output.
 - Time Pulse*-Output is time pulse mode. After output is triggered, it will be activated for the time defined in **Output pulse duration**, after that time output will be restored.
- Output pulse duration:** ON time for output in case of output mode *Timer pulse*.
- Output is:** Output can work in normal or inverted (normally close) mode.
 - Normally open*-In idle mode output pins are in open position.
 - Normally closed*-In idle mode output connections are closed.

Additional output settings - Setting are used to link onboard actions with the outputs if needed:

- **Voice active indication:** When unit reaches voice connection (intercom call) output defined under this section gets activated.
- **Unauthorized call or SMS received:** If unauthorized call or SMS is received on the unit this event will activate output defined under this section.
- **Button pressed indication:** When intercom call button is pressed output defined under this section gets activated.
- **Input 1 activate output:** If input 1 is in alarm mode (**Input operation mode:** *Normal* mode selected) alarm input event on the input will activate output defined under this section.
- **Input 2 activate output:** If input 2 is in alarm mode (**Input operation mode:** *Normal* mode selected) alarm input event on the input will activate output defined under this section.

NOTE

Due to limitation of the outputs use additional outputs settings with care.

8.10 TIMER-TIMED CONTROLLED OUTPUT

SOLO-KP (LCD) unit features 2 timers that can be used to control the Outputs on the unit. Timers can run in day or week mode depending on the selected setting. For each timer user can select which output it will control.




Figure 12: WEB Server-Timer setting →Day mode.




Figure 13: WEB Server-Timer setting →Week mode.

Timer settings:

- **Timer:** Parameter is used to enable and disable the timer function.
- **Mode:** User can select between day or week mode. In day mode the the timer will control on the day table which is the same for all week. In week mode the user can define diffent setting for each day in the week.
- **Timer controls:** Output controlled by the timer function.
- **Output mode:** Output mode management definition.

OUTPUT mode options	Description
Slave mode	The behavior of the outputs (Time pulse or Latching mode) is defined in the Output tab.
Master mode:	When the output is driven by the timer (output is activated by the timer) the outputs are in latching mode regardless of the setting in Output tab. When the output is not activated by the timer, the outputs are working by the defined settings in Output tab.
Output precondition	In this mode Timer is used as PRECONDITION for output control used by other functions like PIN access or Called ID #.

Table 2: WEB Server-Timer setting, output mode options

- **Holidays:** With the definition of the holiday days (use day picker), user can define special behavior on the holiday days.

The described settings are the same for both timers.

8.11 ADMINISTRATION

Administration tab allows user to enable advanced settings: notification of unauthorized access, periodic test messages, lock down of the unit...

Position	Phone number	User name	Input 1	Input 2	Periodic test	Low credit alert	Unauthorised call	Log full	Notify event	
1	8018285058		<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
2			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
3			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
4			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	
5			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	

▼ General settings

Administrator allowed to remote program by SMS: Anyone

Automatic call to administrator 1: Period in days

Automatic periodic test SMS: Period in hours

Test SMS start hour:

Figure 14: WEB Server-Notification numbers

- **Phone number, User name:** Phone number and user name of the user that will be receiving notification messages.
- **Input1, Input2:** If input lines 1 & 2 are defined in alarm mode (**Input operation mode: Normal** mode) and if alarm condition is meet, users with check boxes will receive alarm notification SMS.




Figure 15: WEB Server-Input alarm configuration

- **Periodic test:** User can receive periodic (keep-alive) SMS, tick the check box for the appropriate user. Timer period is defined under parameter **Automatic periodic test SMS**, it is definable in hours.
- **Low credit alert:** In case of prepaid SIM card the unit can notify the user if the credit on the SIM card is low. To enable notification SMS tick the check box in corresponding position. Note that additional input in the **Misc** tab is needed to fully enable credit checking function.

- **Unauthorized call:** In case of unauthorized call the unit can notify user. To enable notification SMS tick the check box in corresponding position.
- **Log full:** Administrator can receive a SMS when LOG event buffer gets at a critical full level.
- **Notify event:** Selection of administrators that will be notified if the notification event is enabled in Temporary pin access tab or Pin access tab.
- **Administration allowed to remote program by SMS:** By selection this option the user can “Lock down” the SOLO-KP (LCD) unit, preventing any unauthorized user to change any configuration on the unit.
- **Automatic call to administrator 1:** To prevent SIM card provider to lock out the SIM card from the network, user can define a periodic call out to telephone number under position 1. Parameter is defined in days (It is not mandatory to set this parameter).
- **Automatic periodic test SMS:** Definition of Time Out for periodic SMS sending.
- **Test SMS start hour:** Periodic SMS, first send-out hour.

8.12 EVENT LOGGING

SOLO-KP (LCD) unit itself supports up to 20000 log events entry. These log events can be pull up to the server by clicking **Read Log** button in the “Event Log” tab. Events are listed in the table.

Event type	Time	User	Output	Extra info	Deleted
Caller id	07.11.2017 11:27:56	Ali	Output 1: ON		<input type="checkbox"/>
Caller id	05.11.2017 13:45:28	Ali	Output 1: ON		<input type="checkbox"/>
PIN access	02.11.2017 16:33:25	Latch	Output 2: OFF		<input type="checkbox"/>
PIN access	02.11.2017 16:25:37	Latch	Output 2: ON		<input type="checkbox"/>
Caller id	31.10.2017 18:49:59	Krissy	Output 1: ON		<input type="checkbox"/>
intercom	30.10.2017 18:49:44	Ali		8015563362	<input type="checkbox"/>
Caller id	29.10.2017	Ali	Output 1: ON		<input type="checkbox"/>

Figure 16: WEB Server-Log event

Each event is equipped with the event type, time, output if triggered and the user name of the user responsible for the event.

If user names are available (Called ID #, PIN codes, Intercom user ...) user name will be shown in the user column.

- **Automatic log clearing:** Behavior if the internal LOG buffer on the unit is FULL of events, unit can CLEAR events or STOP recording new events.
- **Event logging:** User can select between, not logging, logging to internal memory (unit) or optional sending events over units USB connection to the external PC.
- **Automatic log retrieval:** Definition of Time Out period for unit to upload LOG events to the WEB server.
- **Caller ID logging:** Enable/Disable logging of the Caller ID # events.
- **System logging:** Enable/Disable logging of special system events.
- **Alarm input logging:** Enable/Disable logging for input alarm events.
- **Pin access logging:** Enable/Disable of the Pin access and Temporary pin access events.

Output events logging: Enable/Disable of the events triggering the outputs (Timer, Intercom, ...).

NOTE

After events are read and stored to the server, the local copy on the unit gets deleted.

8.13 MISC

This tab is split into 2 sections.




Figure 17: WEB Server-Misc

General settings can be found:

- **SMS text Language:** define the language of the SMS information send out. User can select appropriate language in drop-down menu.
- **Automatic GSM module restart interval:** User can select GSM module restart interval (hours) if needed (Not advisable to use this parameter if not advised otherwise).
- **Self-updating clock:** Parameter is used to allow unit to synchronize to real time. To have the correct time along in log event it is advisable to enable this function.

Prepaid SIM card setting is used the enable credit checking/parsing in case if prepaid SIM card is used. User can select the proper setting by selecting used SIM card provider in the drop down menu in **Provider preset**.

9 WIEGAND INTERFACE DATA FORMATS

SOLO-KP (LCD) unit support standard Wiegand interface, it will work with Wiegand 26bit and Wiegand 30bit protocol and others.

9.1 WIEGAND 26 BIT, DIFFERENT DATA FORMATS

Possible data format:

Mode 0: All 24bit of data are used a decimal representation, no option for facility code

P	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	P
Parity	24Bit card number																						Parity		

	Limits
Card Number	0 - 16777215
Facility Number	None

Table 3: Wiegand 26: Mode 0.

Mode 1: 24bit of data is divided between facility code 8 bits and 16bits for card number

P	F	F	F	F	F	F	F	F	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	P
Parity	8Bit card facility number								16Bit card number																Parity

	Limits
Card Number	0 - 16777215
Facility Number	NOT USED

Table 4: Wiegand 26: Mode 1.

Mode 2: 24bit of data is divided between facility code 8 bits and 16bits for card number

P	F	F	F	F	F	F	F	F	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	P
Parity	8Bit card facility number								16Bit card number																Parity

	Limits
Card Number	0 - 16777215
Facility Number	0 - 255

Table 5: Wiegand 26: Mode 2.

Mode 3: Sections of 4bit data are used as decimals values for number

P	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	P
Parity	Dec. 6				Dec. 5				Dec. 4				Dec. 3				Dec. 2				Dec. 1				Parity

	Limits
Card Number	0 - 99999
Facility Number	None

Table 6: Wiegand 26: Mode 3.

9.2 WIEGAND 30 BIT, DIFFERENT DATA FORMATS

Possible data format:

Mode 0: All 30bit of data are used a decimal representation, no option for facility code

P	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	P
Parity	28Bit card number																												Parity						

	Limits
Card Number	0 - 268435455
Facility Number	None

Table 7: Wiegand 30: Mode 0.

Mode 1: 30bit of data is divided between facility code 8 bits, 16bits for card number and 4bits of unused data.

P	0	0	0	0	F	F	F	F	F	F	F	F	F	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	P
Parity	Not used				8Bit facility number								16Bit card number																Parity						

	Limits
Card Number	0 - 16777215
Facility Number	NOT USED

Table 8: Wiegand 30: Mode 1.

Mode 2: 28bit of data is divided between facility code 8 bits, 16bits for card number and 4bits of unused data.

P	0	0	0	0	F	F	F	F	F	F	F	F	F	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	P
Parity	Not used				8Bit facility number								16Bit card number																Parity						

	Limits
Card Number	0 - 16777215
Facility Number	0 - 255

Table 9: Wiegand 30: Mode 2.

Mode 3: Sections of 4bit data are used as decimals values for number

P	0	0	0	0	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	B	P
Parity	Not Used				Dec. 6				Dec. 5				Dec. 4				Dec. 3				Dec. 2				Dec. 1				Parity							

	Limits
Card Number	0 - 99999
Facility Number	None

Table 10: Wiegand 30: Mode 3.

10 CONTACTS

ONTICO d.o.o.

TEL: 00 386 40 857 338

E-MAIL: info@ontico.eu

WEB SITE: www.ontico.eu

TEHNICAL SUPPORT

Email: info@ontico.eu

SALES

Email: sales@ontico.eu